

## Ports

Ports are available on the computer, network device, and mobile device entity types. Typically, ports are automatically imported into RiskVision by a vulnerability scanner, such as the Tenable Nessus Connector or the Qualys QualysGuard Connector. However, there may be times when you want to manually modify port data.

### To add a port:

1. Open the **Entity Details** page, then click + to expand the **System Details** tab.
2. Click **Ports**.
3. Click **New** to open the **Port** dialog.
4. Enter the following fields:
  - **Name:** The port name.
  - **Protocol:** The type of protocol, such as UDP and TCP.
  - **Protocol Number:** The port number.
  - **Description:** The reason for adding the port.
5. Click **OK**.

### To assign a predefined port:

1. Open the **Entity Details** page, then click + to expand the **System Details** tab.
2. Click **Ports**.
3. Click **Add** to open the **Choose Ports** dialog.
4. Use the following fields to search:
  - **Port Name;**
  - **Port Number;** and
  - **Protocol:** TCP or UDP.

These fields can be used in combination to narrow the search results. <

5. Click **Search** to view results in the **Known Ports** box.
6. Click the port, then click the arrow pointing down to move the port into the **Selected Ports** box.
7. Click **OK**.

### To edit a port:

1. Open the **Entity Details** page, then click + to expand the **System Details** tab.
2. Click **Ports**.
3. Select the box in the corresponding port row. You can only edit user-defined and scanner-imported ports.
4. Click **More Actions** > **Edit** to open the **Port** dialog.
5. Edit the port, as needed.

6. Click **OK**.

## To delete a port:

1. Open the **Entity Details** page, then click + to expand the **System Details** tab.
2. Click **Ports**.
3. Select the box in the corresponding port row.
4. Click **Delete**.

Manually modified port information will be overwritten by scanner data, if it applies to the same entity.