

# Ports

Ports are available on the Computer, Network Device, and Mobile Device entity types. Typically, ports are automatically imported into RiskVision by a vulnerability scanner, such as the Tenable Nessus Connector or the Qualys QualysGuard Connector. However, there may be times when you may want to manually modify port data.

## To add a port

1. In the entity details page, click + to expand the **System Details** tab, and click **Ports**.
2. Click **New**. The **Port** dialog appears.
3. In the **Port** dialog, enter the following fields:
  - **Name**. Enter the port name.
  - **Protocol**. Enter the type of protocol, such as UDP and TCP.
  - **Protocol Number**. Enter the port number.
  - **Description**. Enter the information that helps understand the purpose of adding the port.
4. Click **OK**. The port is added.

## To assign a predefined port:

1. In the entity details page, click + to expand the **System Details** tab, and click **Ports**.
2. Click **Add**. The **Choose Ports** dialog appears.
3. In the dialog, use the following fields to search the port:
  - Port Name. Enter the port's name.
  - Port Number. Enter the port's number.
  - Protocol. Enter the protocol, such as TCP or UDP.
4. The fields above can be used in combination to narrow the search results.
5. Click **Search** after entering the search field(s).
6. The results are returned and displayed in the **Known Ports** box. If the search returns too many ports, use the scroll-bar to find the port.
7. After you locate the port, select the port in the **Known Ports** box, and click the arrow pointing downwards to move the port into the **Selected Ports** box.
8. Click **OK**. The predefined port is added.

## To edit a port:

1. In the entity details page, click + to expand the **System Details** tab, and click **Ports**.
2. Select the box in the corresponding port row. You can edit only the user-defined and scanner-imported ports
3. Select **Edit** in the More Actions drop-down list. The **Port** dialog appears, where changes to the port can be made.
4. Click **OK** after the completion of changes.

## To delete a port:

1. In the entity details page, click + to expand the **System Details** tab, and click **Ports**.
2. Select the box in the corresponding port row and click **Delete**. The selected port is removed from the entity.

Manually modified port information will be overwritten by scanner data if the scanner data pertains to the same entity.